

Marked up Specification

09/554905

526 Rec'd PCT/PTO 22 MAY 2000

SUBSTITUTE SPECIFICATION

DOCKET NO: 9847-0048-6X\*PCT

ENKEL 8335

5

TITLE OF THE INVENTION

A METHOD AND A SYSTEM FOR SPEED CONTROL OF A ROTATING  
ELECTRICAL MACHINE WITH FLUX COMPOSED OF TWO QUANTITIES

10

CROSS REFERENCE TO RELATED PATENT DOCUMENTS

The present document is based on published international patent application  
No. WO 99/29034, the entire contents of which being incorporated herein by reference.

15

BACKGROUND OF THE INVENTION

Field of the Invention

20

~~According to a first aspect,~~ The present invention relates to a system and a  
method for the adaptation, optimization, and/or control of the speed of a rotating electric  
machine ~~included in the system, which machine is intended to be directly connected to a~~  
distribution or transmission network.

~~According to a second aspect of the present invention, it relates to a method for  
speed control of a rotating electric machine, which machine is intended to be directly con-  
nected to a distribution or transmission network.~~

25

Discussion of the Background:

The rotating electric machine which occurs in the present invention may be, for  
example, a synchronous machine, an asynchronous machine, a double-fed machine, an  
asynchronous converter cascade, an external pole machine or a synchronous flux machine.

30

To connect machines of this kind to distribution or transmission networks, hith-  
erto transformers have been used for step-up transformation of the voltage to network  
level, that is, to the range of 130-400 kV.

Generators with a rated voltage of up to 36 kV are described by Paul R. Siedler,  
"36 kV Generators Arise from Insulation Research", Electrical World, 15 October 1932,

09554905.072600

pages 524-537. These generators ~~comprise~~ have windings of high-voltage cable, wherein the insulation is divided into different layers with different dielectric constants. The insulating material used ~~comprises~~ is commonly formed of different combinations of the three components, namely, mica, foil-mica, varnish, and paper.

5 Now, it has ~~proved~~ been shown that by manufacturing windings of ~~the~~ machine, ~~mentioned in the introduction, of using~~ an insulated electric high-voltage conductor with a solid insulation ~~of a similar kind~~ such as used in cables for power transmission, the voltage of the machine may be increased to ~~such~~ levels such that the machine may be directly connected to any power network without intermediate transformers. A typical operating range  
10 for these machines is 30-800 kV.

The insulated conductor or high-voltage cable which is used in the present invention is flexible and of the kind described in more detail in PCT applications SE97/00874 (WO 97/45919) and SE97/00875 (WO 97/45847). A further description of the insulated conductor or cable is to be found in PCT-applications SE97/00901 (WO 97/45918),  
15 SE97/00902 (WO 97/45930) and SE97/00903 (WO 97/45931).

In the device according to the invention, the windings are preferably of a kind corresponding to cables with a solid extruded insulation which are currently used for power distribution, for example so-called XLPE cables or cables with EPR insulation. Such a cable ~~has~~ comprises an inner conductor composed of one or more strands, an inner semiconductor layer surrounding the conductor, a solid insulating layer surrounding the semiconductor layer, and an outer semiconducting layer surrounding the insulating layer. Such cables are flexible, which is an important property in this context since the technology for the device according to the invention is primarily based on a winding system where the winding is made with wires which are drawn back and forth a plurality of turns, that is, without  
20 joints in the coil ends which are required when the winding in the core ~~contains~~ consists of stiff conductors. An XLPE cable normally has a flexibility corresponding to a radius of curvature of about 20 cm for a cable with a diameter of 30 mm and a radius of curvature of about 65 cm for a cable with a diameter of 80 cm. The expression "flexible" in this context ~~application~~ thus ~~means~~ indicates that the winding is flexible down to a radius of curvature in the order of magnitude of 8-25 times the cable diameter.  
25  
30

The winding should be made such that it may maintain its properties also when being bent and when, during operation, it is subjected to thermal stresses. It is of great im-

0954905-072600

portance in this connection that the layers maintain their adhesion to one another. Of decisive importance in this connection are the material properties of the layers, above all their elasticities and their relative coefficients of thermal expansion. For an XLPE cable, for example, the insulating layer is of crosslinked low-density polyethylene and the semiconducting layers of polyethylene with soot and metal particles mixed therein. Volume changes as a result of temperature variations are absorbed entirely as changes in radius in the cable, and because of the comparatively slight difference in the coefficients of thermal expansion of the layers in relation to the elasticities of these materials, the radial expansion of the cable will be able to take place without the layers loosening or delaminating from each other.

The material combinations described above are only to be considered as examples. The scope of the invention of course ~~comprises also~~ includes other combinations which fulfil the conditions mentioned and which fulfil the conditions of being semiconducting, that is, with a mass resistivity in the range  $1-10^5 \text{ } \Omega\text{-cm}$ , and of being insulating, that is, with a mass resistivity greater than  $10^5 \text{ } \Omega\text{-cm}$ , respectively.

The insulating layer may, for example, be formed in whole or in part of ~~comprise a~~ solid thermoplastic material such as low-density polyethylene (LDPE), high-density polyethylene (HDPE), polypropylene (PP), polybutylene (PB), polymethyl pentene (PMP), crosslinked materials such as crosslinked polyethylene (XLPE) or rubber, such as ethylene-propylene rubber (EPR) or silicone rubber.

The inner and outer semiconducting layers may have the same base materials but mixed with particles of conducting materials, such as soot or metal powder.

The mechanical properties of these materials, primarily their coefficients of thermal expansion, are influenced to a rather slight extent by whether they are ~~it is~~ mixed with soot or metal powder or not. The insulating layer and the semiconducting layers will thus have substantially largely the same coefficients of thermal expansion.

For the semiconducting layers, also ethylene vinyl acetate copolymer/nitrile rubber, butyl-grafted polyethylene, ethylene acrylate copolymer, ethylene ethyl acrylate copolymer and ethylene butyl acrylate copolymer may constitute suitable polymers.

\_\_\_\_\_Also when different layers of materials are used as a base in the respective layers, it is desirable for their coefficients of thermal expansion to be of the same order of magnitude. This is true of the combination of the materials listed above.

- 5 \_\_\_\_\_The materials listed above have quite a good elasticity which is sufficient for any minor deviations in the coefficients of thermal expansion of the materials in the layers to be taken up in the radial direction of the elasticity such that cracks or other damage do not arise and such that the layers do not become detached from each other.

10 The conductivity of the two semiconducting layers is sufficiently great to substantially equalize the potential along the respective layer. At the same time, the conductivity is so low that the outer semiconducting layer has sufficient resistivity to enclose or contain the electric field in the cable.

15 Each of the two semiconducting layers thus essentially constitutes an equipotential surface and the winding with these layers will substantially enclose the electric field within it.

It is, of course, not excluded that one or several further semiconducting layers may be arranged in the insulating layer.

20 It is previously known to achieve a more efficient and flexible operation of hydroelectric power stations/pump storage plants with, for example, VARSPEED generators, and that each turbine has an optimum working point, at which speed, net head and water flow are adapted to one another to give maximum efficiency. For large machines, the speed may be controlled in several ways, for example by pole switching, stator supply and frequency adaptation ~~by means through the use~~ of frequency converters or ~~by means~~ of a sub- and supersynchronous converter cascade which feeds an asynchronous machine from two  
25 directions, that is, both via a stator and a rotor. The rotating three-phase rotor winding and the stationary frequency converter equipment for control of the rotor flux and hence the slip frequency for speed optimization take place via slip rings.

Use of slip rings in speed optimization entails a number of disadvantages such as wear, fouling and hence increased maintenance costs.

## SUMMARY OF THE INVENTION

The object of the present invention is to solve the above-mentioned problems. This is achieved with a system for adaptation/optimization of the speed of a rotating electric machine included in the system ~~according to claims 1 and 9~~, and with a method for speed control of a rotating electric machine as described herein ~~according to claims 18 and 19~~. The machine included in the system according to a first embodiment of the present invention ~~comprises~~ has at least two electric windings, each of which ~~comprises~~ is formed from at least one electric conductor, a first semiconducting layer arranged surrounding the conductor, an insulating layer arranged surrounding the first semiconducting layer, and a second semiconducting layer arranged surrounding the insulating layer. In addition, the system ~~comprises means~~ has mechanisms which generate the resultant stator and air gap flux of the machine ~~during~~ in operation, ~~where the~~ which flux is composed of at least two vectorial quantities.

One advantage of the system according to the present invention is that no slip rings occur, which, inter alia, entails simplified maintenance and no losses as a result of brush voltage drop. In addition, a rapid demagnetization in case of fault may be obtained.

An advantageous embodiment of the system is obtained in accordance with the invention in that the potential of the first semiconducting layer is essentially equal to the potential of the conductor.

In connection therewith, it is an advantage if the second semiconducting layer is arranged to form essentially an equipotential surface, surrounding the conductor.

An additional advantage in this connection is obtained if the second semiconducting layer is connected to a predetermined potential.

In connection therewith, it is an advantage if the predetermined potential is ground potential.

A further advantage in connection therewith is obtained if at least two adjacent layers of the windings of the machine have essentially equal coefficients of thermal expansion.

In connection therewith, it is an advantage if the conductor ~~comprises~~ has a number of strands, of which at least some are in electric contact with one another.

A further advantage in connection therewith is obtained if each one of the three layers mentioned is secured to adjacent layers along essentially the whole contact surface.

09554905 072600

According to a second embodiment of the system according to the invention, the machine included in the system ~~comprises~~ includes at least two electric winding, each of which ~~being~~ is formed from a high-voltage cable ~~comprising~~ having one or more current-carrying conductors, each conductor exhibiting a number of strands, a first semiconducting layer arranged around each conductor, an insulating layer of solid insulating material arranged around the first semiconducting layer, and a second semiconducting layer arranged around the insulating layer. In addition, the system ~~comprises~~ means has a mechanism which generates the resultant stator and air gap flux of the machine in operation, which flux is composed of at least two vectorial quantities.

One advantage of the system according to the second embodiment of the present invention is that no slip rings occur, which, inter alia, entails simplified maintenance and no losses as a result of brush voltage drop. In addition, a rapid demagnetization in case of fault may be obtained.

An additional advantage in connection therewith is obtained if the insulating conductor or the high-voltage cable is flexible.

In connection therewith, it is an advantage if the layers are arranged to adhere to one another even if the insulating conductor or the high-voltage cable is bent.

An additional advantage in connection therewith is that the flux-generating member ~~comprises~~ has an extra winding arranged on the machine and magnetization equipment connected to the machine, whereby one flux vector is generated via the extra winding and the magnetization equipment and one flux vector is generated via the ordinary winding of the machine.

In connection therewith, it is an advantage if the magnetization equipment ~~consists~~ contains of a first frequency converter.

An additional advantage in this connection is obtained if the system furthermore ~~comprises~~ has an auxiliary feeder connected to the first frequency converter and the machine.

In connection therewith, it is an advantage if the machine ~~comprises~~ is formed from an asynchronous rotor, and if the auxiliary feeder ~~comprises~~ has a stator winding and a permanent-magnet rotor connected to the asynchronous rotor.

An additional advantage in connection therewith is obtained if the system furthermore ~~comprises~~ has a transformer connected to the first frequency converter and the

09554905-072600

auxiliary feeder, ~~where the~~<sup>which</sup> transformer is connected to a distribution busbar via a first circuit breaker, and a second frequency converter connected to the transformer, ~~where the~~<sup>which</sup> second frequency converter is connected to the distribution busbar via a second circuit breaker.

5 In connection therewith, it is an advantage if the windings are flexible and if the mentioned layers make contact with one another.

An additional advantage in this connection is if the mentioned layers are of materials with such elasticities and such a relation between the coefficients of thermal expansion of the materials that the volume changes of the layers, caused by temperature variations during operation, are capable of being absorbed by the elasticity of the materials such  
10 that the layers ~~retain their~~<sup>remain in</sup> contact with one another at the temperature variations which occur during operation.

In connection therewith, it is an advantage if the materials in the layers mentioned have a high elasticity.

15 An additional advantage in connection therewith is obtained if each semiconducting layer constitutes essentially an equipotential surface.

The method according to a first embodiment of the present invention for speed control of a rotating electric machine is applicable to a machine which is intended to be directly connected to a distribution or transmission network. The machine ~~comprises is~~  
20 ~~formed from~~ at least two electric windings, each of which ~~comprises has~~ at least one electric conductor, a first semiconducting layer arranged surrounding the conductor, an insulating layer arranged surrounding the first semiconducting layer, and a second semiconducting layer arranged surrounding the insulating layer. The method ~~includes comprises~~  
25 the step of generating at least two vectorial quantities which constitute the resultant stator and air gap flux of the machine during operation.

The method according to a second embodiment of the present invention for speed control of a rotating electric machine is applicable to a machine which is intended to be directly connected to a distribution or transmission network. The machine ~~has comprises~~ at least two electric windings, which are each formed from a high-voltage cable ~~having comprising~~  
30 ~~prising~~ one or more current-carrying conductors, whereby each conductor exhibits a number of strands, a first semiconducting layer arranged around each conductor, an insulating layer of solid insulating material arranged around the first semiconducting layer, and a sec-

009270504550

ond semiconducting layer arranged around the insulating layer. The method ~~includes~~com-  
~~prises~~ the step of generating at least two vectorial quantities which constitute the resultant  
 stator and air gap flux of the machine during operation.

5 An advantage of the method according to the two embodiments of the present in-  
 vention is that no slip rings occur, which, inter alia, entails simplified maintenance and no  
 losses as a result of brush voltage drop. In addition, a rapid demagnetization in case of fault  
 may be obtained.

In connection therewith, an advantage is obtained if the method ~~includes~~comprises  
 the following additional step:

- 10 • controlling at least one of the vectorial fluxes with respect to phase position as well as  
 amplitude and speed of rotation relative to the flux generated and rotated by the con-  
 necting network.

A further advantage in connection therewith is obtained if the method ~~comprises~~  
includes the following steps:

- 15 • generating a flux vector via an extra winding, mounted on the stator of the machine, and  
 magnetization equipment connected to the machine, and  
 • generating a flux vector via the ordinary winding of the machine.

20 According to a first aspect of the invention, the rotating electric machine ~~com-~~  
~~prises~~ additionally includes, in addition, an asynchronous rotor, whereby the flux control  
 is used for speed-control of the machine in generator operating mode.

According to a second aspect of the invention, the rotating electric machine ~~com-~~  
~~prises, in addition,~~ additionally includes an asynchronous rotor, whereby the flux control is  
 used for speed-control of the machine in motor operating mode.

25 According to a third aspect of the present invention, the flux control is used to  
 suppress the harmonic content of the stator voltage in the ordinary stator winding of the  
 machine.

30 According to a fourth aspect of the present invention, the reactive magnetization  
 current of the machine is injected via the extra winding, which makes possible control of  
 the voltage of the machine on the ordinary winding of the machine both for a non-mains-  
 connected and a mains-connected machine.

0954905 " 072600

In connection therewith, it is an advantage if the rotating electric machine furthermore ~~comprises~~ includes a permanent-magnet rotor, connected to the asynchronous rotor, for generating magnetization current and other auxiliary power.

According to a further aspect of the present invention, the flux control is used for interruption-free change from generator operating mode to motor operating mode and vice versa.

In connection therewith, it is an advantage if the resultant flux in the machine is:

$$\Phi = \Phi_1 + \Phi_2 \quad (\text{Komplettera med vektorstreck-t})$$

where  $\Phi_1$  is the rotating flux on the stator side of the machine and  $\Phi_2$  is the flux generated by the rotor current, whereby

$$\Phi_1 = \Phi_{\text{Imagn}} + \Phi_{\text{Istator}} \quad (\text{Komplettera med vektorstreck-t})$$

where  $\Phi_{\text{Istator}}$  is the rotating flux generated by the current in the ordinary winding, whereby the speed of rotation on  $\Phi_{\text{Istator}}$  is dependent on the frequency of the network and the number of pole pairs in the machine, and  $\Phi_{\text{Imagn}}$  is the rotating flux generated by the current in the extra winding, which flux is controllable with respect to phase position as well as amplitude and frequency relative to the flux vector of the ordinary winding.

An additional advantage in connection therewith is obtained if the vectorially created flux in the machine is controlled with the aid of the relative phase position as well as the relative amplitude value between the active and reactive current values of the ordinary winding (54) and the extra winding (56).

### **BRIEF DESCRIPTION OF THE DRAWINGS**

The invention will now be explained in greater detail by the following description of preferred embodiments of the invention with reference to the accompanying drawings.

Figure 1 is a cross-section view of a high-voltage cable;

Figure 2 is a diagram which shows a system according to the present invention for adaptation/optimization of the speed of a rotating electric machine included in the system;

Figures 3a and 3b are schematic figures which more clearly show the solution on principle for the system shown in Figure 2;

09554905.072600

Figures 4a and 4b are schematic figures which for the purpose of clarification show, respectively, the rotating fluxes and the electromotive force (EMF) induced in the rotor part in the system shown in Figure 2;

Figures 5a, 5b and 5c are three diagrams which illustrate the principle of control/change of the speed of rotation for the resultant flux in the machine in the system shown in Figure 2; and

Figure 6 is a flow diagram of the method according to the present invention for speed control of a rotating electric machine.

### **DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS**

Figure 1 shows a cross-section view of a high-voltage cable 10 which is traditionally used for transmission of electric power. The high-voltage cable 10 shown may, for example, be a standard XLPE cable 145 kV but without a sheath of screen. The high-voltage cable 10 ~~comprises~~ has an electric conductor, which may ~~comprise~~ have one or more strands 12 of circular cross section of, for example, copper (Cu). These strands 12 are arranged in the centre of the high-voltage cable 10. Around the strands 12 there is a first semiconducting layer 14. Around the first semiconducting layer 14 there is an insulating layer 16, for example XLPE insulation. Around the insulating layer 16 there is a second semiconducting layer 18. In the high-voltage cable 10 shown, the three layers 14, 16, 18 are designed so as to adhere to one another also when the cable 10 is bent. The shown cable 10 is flexible and this property is retained in the cable 10 during its service life.

Figure 2 shows a diagram of a system according to the present invention for adaptation/optimization of the speed of a rotating electric machine included in the system. The system 20 ~~comprises~~ includes a rotating electric machine 22, which is directly connected to a distribution or transmission network 24. The rotating electric machine 24 ~~comprises~~ has at least two windings, wherein each winding in a first embodiment of the present invention ~~contains~~ comprises at least one conductor, a first semiconducting layer arranged surrounding the conductor, an insulating layer arranged surrounding the first semiconducting layer, and a second semiconducting layer arranged surrounding the insulating layer. According to a second embodiment of the system 20 according to the present invention, the windings are each formed from the high-voltage cable 10 shown in Figure 1. The system 20 ~~comprises, in addition,~~ additionally has a member 26 which generates the resul-

09554905-072600

tant stator and air gap flux of the machine in operation, which flux is composed of at least two vectorial quantities. In addition, the system 20 ~~comprises-contains~~ magnetization equipment 28, connected to the rotating electric machine 22, which in the shown example is in the form of a first frequency converter 28. Connected to the rotating electric machine 22 is an auxiliary feeder 30. In addition, the system 20 ~~comprises-has~~ a transformer 32 for voltage adaptation, connected to the first frequency converter 28 and the auxiliary feeder 30. The transformer 32, in its turn, is connected to a distribution busbar 36 via a first circuit breaker 34. In addition, the system 20 ~~comprises-has~~ a second frequency converter 38 for auxiliary power generation, which second frequency converter 38 is connected, on the one hand, to the transformer 32 and, on the other hand, to the distribution busbar 36 via a second circuit breaker 40.

Figures 3a and 3b schematically show the solution on principle for the system 20 shown in Figure 2. Figure 3a shows the rotor 50 and the stator 52, respectively, of the rotating electric machine 22. The stator 52 is provided in traditional manner with a three-phase winding 54, also called ordinary winding 54 or main winding 54. In addition, the stator 52 is provided with an extra winding 56. When the rotating electric machine 22 is in operation, a rotating flux  $\Phi_1$ , among other things, is generated on the stator side, which flux  $\Phi_1$  rotates in the direction of the dotted arrow. Figure 3b shows a part of the system 20 shown in Figure 2 which is of importance to the present invention. Again, the main winding 54 (three-phase) and the extra winding 56 (three-phase) of the stator are shown, the extra winding 56 being connected to the first frequency converter 28. In addition, the stator winding 58 (three-phase) of the auxiliary feeder 30 (cf. Fig. 2) is shown, which is also connected to the first frequency converter 28. The rotating electric machine 22 (cf. Fig. 2) ~~comprises, in addition, additionally includes~~ an asynchronous rotor 60 for the main winding 54 and the extra winding 56 of the stator. In addition, Figure 3b shows a permanent-magnet rotor 62 included in the auxiliary feeder 30 (cf. Fig. 2). The permanent-magnet rotor 62 is connected to the asynchronous rotor 60 so that these rotate together. The system 20 may be used for adaptation/optimization of the speed of a rotating electric machine 22 included in the system 20. This is achieved by composing the rotating flux  $\Phi_1$  on the stator side 52 (cf. Fig. 3) from at least two flux vectors. One flux vector is generated in traditional manner via the main winding 54 of the stator 52 and one flux vector is generated via the extra winding 56 of the stator 52 and the first frequency converter 28. By controlling the

0954905-072600

flux vector, generated via the extra winding 56 and the first frequency converter 28, with respect to phase position as well as amplitude and frequency relative to the flux vector generated via the main winding 54, the angular velocity of the total flux vector may rotate both supersynchronously and subsynchronously related to the flux vector generated via the main winding.

Figures 4a and 4b schematically show the rotating fluxes and the EMF induced in the rotor part, respectively, in the system shown in Figure 2. Figure 4a again shows parts of the rotating electric machine 22 (cf. Fig. 2) in the form of the rotor 50 and the stator 52. As is also clear from Figure 3a, the stator 52 is provided with a main winding 54 and an extra winding 56. The rotor 50 rotates in the direction of the arrow A. The rotating total flux  $\Phi_1$  of the stator 52 rotates in the direction of the arrow B with the speed  $n_{\Phi_1}$ . The total generated flux for the machine 22 in operation is

$$\Phi = \Phi_1 + \Phi_2 \quad (\text{Komplettera med vektorstreck})$$

where  $\Phi_1$  is the rotating flux on the stator side, and  $\Phi_2$  is the flux generated by the rotor current. The rotating flux  $\Phi_1$  on the stator side may be expressed as follows

$$\Phi_1 = \Phi_{1\text{magn}} + \Phi_{1\text{stator}} \quad (\text{Komplettera med vektorstreck})$$

where  $\Phi_{1\text{stator}}$  is the rotating flux generated by the current in the main winding 54, and  $\Phi_{1\text{magn}}$  is rotating and controllable flux.  $\Phi_{1\text{magn}}$  is generated via the extra winding 56 of the stator 52 and the first frequency converter 28. Figure 4b schematically shows the rotor 50. The rotating air gap flux induces a winding EMF,  $e_{\text{rotor}}$ , in the rotor winding. The rotor current,  $I_{\text{rotor}}$ , driven by the EMF  $e_{\text{rotor}}$  gives rise to a torque  $M_v$ . The winding EMF  $e_{\text{rotor}}$  may be expressed as

$$e_{\text{rotor}} = k_1 \times \Phi_1 \times (n_{\text{rotor}} - n_{\Phi_1})$$

The torque may be expressed as

$$M_v = k_2 \times \Phi_1 \times I_{\text{rotor}}$$

where  $k_1$ ,  $k_2$  are constants,  $n_{\text{rotor}}$  is the speed of the rotor 50, which may be changed and adapted for optimization of, for example, the efficiency of the turbine, and  $n_{\Phi_1}$  is the speed of the rotating flux  $\Phi_1$  on the stator side, whereby the speed  $n_{\Phi_1}$  may be changed and adapted for slip optimization.

Figures 5a, 5b and 5c show three different diagrams which illustrate the principle of control/change of the speed of rotation for the resultant flux  $\Phi_1$  on the stator side in the

machine 22 in the system 20 shown in Figure 2. Figure 5a shows how  $\Phi_{1stator}$  varies with the time t. The speed of rotation of  $\Phi_{1stator}$  depends on the frequency of the network (cf. Fig. 2) and the number of pole pairs in the rotating electric machine 22. Figure 5b shows how  $\Phi_{1magn}$  varies with the time t. The amplitude, frequency and phase position of  $\Phi_{1magn}$  are determined with respect to the desired speed of rotation of  $\Phi_1$ . Figure 5c shows how the resultant rotating flux  $\Phi_1$  in the stator 52 varies with the time t.

Figure 6 shows a flow diagram of the method according to the present invention for speed control of a rotating electric machine. The method according to the present invention ~~comprises~~ includes a number of steps which will be described below. The flow diagram starts at block 70. The next step, at block 72, ~~comprises~~ includes starting and connecting the rotating electric machine 22 to the network (cf. Fig. 2). Thereafter, at block 74, at least two vectorial quantities are generated, which constitute the resultant stator and air gap flux of the machine in operation. Provided that there are two vectorial quantities, one flux vector  $\Phi_{1stator}$  is generated via the main winding 54 of the stator 52, and one flux vector  $\Phi_{1magn}$  is generated via the extra winding 56 of the stator 52 and the first frequency converter 28. Thereafter, at block 76, it is inquired whether the speed of the machine is suitable. If the question is answered in the affirmative, block 76 is reiterated. On the other hand, if the answer is negative, the method continues to block 78. In block 78, the step of controlling at least one of the vectorial fluxes with respect to phase position as well as amplitude and frequency (speed of rotation) relative to the flux generated and rotated by the connecting network is carried out. This control implies that the machine has the desired/appropriate speed. Thereafter, at block 80, it is inquired whether the machine is to be in operation. If the question is answered in the affirmative, block 76 is reiterated. On the other hand, if the answer is negative, the method continues to block 82. At block 82, the operation of the machine is stopped. At block 84, the method is terminated.

The invention is not limited to the embodiments shown but several modifications are feasible within the scope of the inventive concept. Thus adaptation of the slip frequency may take place both during motor and generator operation and by suitable dimensioning of the frequency converter equipment, all operating modes may, in principle, be met.

In addition, the principle may be applied to rapid, interruption-free change from motor operation to generator operation in, for example, industrial applications.

Further, the principle may be applied to reduction/elimination of the harmonic content in the stator voltage of a machine. The principle may be applied to both synchronous and asynchronous machines.

5 In addition, the frequency converter equipment and the extra winding of the stator may be used both when starting the machine upon start-up and when braking the machine upon shutdown.

Further, the angular velocity of the flux vector generated via the extra winding is controllable via the stationary frequency converter equipment and hence an optimum operating position for adaptation to a changed turbine speed caused by changed net head may  
10 always occur.

In addition, the vectorially created flux in the machine may be controlled with the aid of the relative phase position as well as the relative amplitude position between the active and reactive current values of the ordinary winding and the extra winding.

The invention is not limited to the embodiments shown, but several variants are  
15 feasible within the scope of the appended claims.

---

0954905-072600

## CLAIMS

1. A system (20) for adaptation/optimization of the speed of a rotating electric machine (22) included in the system (20), which machine (22) is intended to be directly connected to a distribution or transmission network (24) and comprising at least two electric windings, characterized in that the winding each comprises at least one electric conductor, a first semiconducting layer (14) arranged surrounding the conductor, an insulating layer (16) arranged surrounding the first semiconducting layer (14), and a second semiconducting layer (18) arranged surrounding the insulating layer (16), and that the system (20) comprises ~~means~~ mechanisms (26) which generate the resultant stator and air gap flux of the machine (22) during operation, which flux is composed of at least two vectorial quantities.
2. A system (20) according to claim 1, characterized in that the potential of the first semiconducting layer (14) is essentially equal to the potential of the conductor.
3. A system (20) according to claim 1 or 2, characterized in that the second semiconducting layer (18) is adapted to form essentially one equipotential surface, surrounding the conductor.
4. A system (20) according to claim 3, characterized in that the second semiconducting layer (18) is connected to a predetermined potential.
5. A system (20) according to claim 4, characterized in that said predetermined potential is ground potential.
6. A system (20) according to any of the preceding claims, characterized in that at least two adjacent layers of the windings of the machine have essentially identical coefficients of thermal expansion.
7. A system (20) according to any of the preceding claims, characterized in that the conductor comprises a number of strands (12), at least some of which are in electric contact with one another.

8. A system (20) according to any of the preceding claims, characterized in that each of said three layers is secured to adjacent layers along essentially the whole contact surface.

5 9. A system (20) for adaptation/optimization of the speed of a rotating electric machine (22) included in the system (20), which machine is intended to be directly connected to a distribution or transmission network (24) and comprising at least two electric windings, characterized in that the windings are each formed from a high-voltage cable (10) comprising one or more current-carrying conductors, whereby each conductor exhibits a  
10 number of strands (12), a first semiconducting layer (14) arranged around each conductor, an insulating layer (16) of solid insulating material arranged around said first semiconducting layer (14), and a second semiconducting layer (18) arranged around the insulating layer (16), and that the system (20) comprises means (26) which generate the resultant stator and air gap flux of the machine (22) in operation, which flux is composed of at least  
15 two vectorial quantities.

10. A system (20) according to any of the preceding claims, characterized in that the insulating conductor or high-voltage cable (10) is flexible.

20 11. A system (20) according to claim 10, characterized in that the layers are arranged to adhere to one another also when the insulated conductor or high-voltage cable (10) is bent.

12. A system (20) according to any of the preceding claims, characterized in that the  
25 flux-generating member (26) comprises an extra winding (56), arranged on the stator (52) of the machine (22), and magnetization equipment (28) connected to the machine (22), whereby one flux vector is generated via the extra winding (56) and the magnetization equipment (28) and one flux vector is generated via the ordinary winding (54) of the machine (22).

30 13. A system (20) according to claim 12, characterized in that the magnetization equipment (28) is in the form of a first frequency converter (28).

009220 5064560

14. A system (20) according to claim 13, characterized in that the system (20), in addition, comprises an auxiliary feeder (30) connected to the first frequency converter (28) and the machine (22).

15. A system (20) according to claim 14, characterized in that the machine (22) comprises an asynchronous rotor (60) and that the auxiliary feeder (30) comprises a stator winding (58) and a permanent-magnet rotor (62) connected to the asynchronous rotor (60).

16. A system (20) according to any of claim 14 or 15, characterized in that the system (20), in addition, comprises a transformer (32) connected to the first frequency converter (28) and the auxiliary feeder (30), said transformer being connected to a distribution busbar (36) via a first circuit breaker (34), and a second frequency converter (38) which is connected to the transformer (32) and which is connected to the distribution busbar (36) via a second circuit breaker (40).

17. A system (20) according to claim 1, characterized in that the windings are flexible and in that said layers make contact with one another.

18. A system (20) according to claim 17, characterized in that said layers are of a material with such elasticity and such a relation between the coefficients of thermal expansion of the materials that the volume changes of the layers, caused by temperature variations during operation, are capable of being absorbed by the elasticity of the materials such that the layers retain their contact with one another at the temperature variations which occur during operation.

19. A system (20) according to claim 18, characterized in that the materials in said layers have a high elasticity.

20. A system (20) according to claim 18, characterized in that each semiconducting layer constitutes essentially an equipotential surface.

09554905-072600

21. A method for speed control of a rotating electric machine (22), which machine (22) is intended to be directly connected to a distribution or transmission network (24) and comprising at least two electric windings, each winding comprising at least one electric conductor, a first semiconducting layer (14) arranged surrounding the conductor, an insulating layer (16) arranged surrounding the first semiconducting layer (14), and a second semiconducting layer (18) arranged surrounding the insulating layer (16), which method comprises the following step:

- generating at least two vectorial quantities which constitute the resultant stator and air gap flux of the machine (22) during operation.

22. A method for speed control of a rotating electric machine (22), which machine (22) is intended to be directly connected to a distribution or transmission network (24) and comprising at least two electric windings, each winding being formed of a high-voltage cable (10) comprising one or more current-carrying conductors, whereby each conductor exhibits a number of strands, a first semiconducting layer (14) arranged around each conductor, an insulating layer (16) of solid insulating material arranged around said first semiconducting layer (14), and a second semiconducting layer (18) arranged around the insulating layer (16), which method comprises the following step:

- generating at least two vectorial quantities which constitute the resultant stator and air gap flux of the machine (22) during operation.

23. A method according to any of claim 21 or 22, which method is characterized by the following additional step:

- controlling at least one of the vectorial fluxes with respect to phase position as well as amplitude and speed of rotation relative to the flux generated and rotated by the connecting network (24).

24. A method according to claim 23, characterized by the following steps:

- generating a flux vector via an extra winding (56), mounted on the machine (22), and magnetization equipment (28) connected to the machine (22), and
- generating a flux vector via the ordinary winding (54) of the machine (22).

09554905-072600

25. A method according to any of claim 23 or 24, characterized in that the rotating electric machine (22), in addition, comprises an asynchronous rotor (60), whereby the flux control is used for speed control of the machine (22) in generator operating mode.

5 26. A method according to any of claim 23 or 24, characterized in that the rotating electric machine (22), in addition, comprises an asynchronous rotor (60), whereby the flux control is used for speed control of the machine (22) in motor operating mode.

10 27. A method according to any of claim 23 or 24, characterized in that the flux control is used for damping the harmonic content of the stator voltage in the ordinary winding (54) of the machine (22).

15 28. A method according to claim 24, characterized in that the reactive magnetization current of the machine (22) is injected via the extra winding (56), whereby it is possible to control the voltage of the machine (22) on the ordinary winding (54) of the machine (22) for both a non-mains-connected and a mains-connected machine (22).

20 29. A method according to claim 25, characterized in that the rotating electric machine (22), in addition, comprises a permanent-magnet rotor (62), connected to the asynchronous rotor (60), for generating magnetization current and other auxiliary power.

30. A method according to any of claim 23 or 24, characterized in that the flux control is used for interruption-free change from generator operating mode to motor operating mode and vice versa.

25 31. A method according to any of claims 24-30, characterized in that the resultant flux in the machine (22) is

$$\Phi = \Phi_1 + \Phi_2 \quad (\text{Komplettera med vektorstreck !})$$

30 where  $\Phi_1$  is the rotating flux on the stator side of the machine and  $\Phi_2$  is the flux generated by the rotor current, whereby

$$\Phi_1 = \Phi_{1\text{magn}} + \Phi_{1\text{stator}} \quad (\text{Komplettera med vektorstreck !})$$

where  $\Phi_{1\text{stator}}$  is the rotating flux generated by the current in the ordinary winding

09554905-072600

(54), whereby the speed of rotation on  $\Phi_{\text{stator}}$  is dependent on the frequency of the network and the number of pole pairs in the machine (22), and  $\Phi_{\text{magn}}$  is the rotating flux generated by the current in the extra winding (56), which flux is controllable with respect to phase position as well as amplitude and frequency relative to the flux vector of the ordinary winding (54).  
5

32. A method according to claim 24, characterized in that the vectorially created flux in the machine (22) is controlled with the aid of the relative phase position as well as the relative amplitude value between the active and reactive current values of the ordinary winding (54) and the extra winding (56).  
10

---

009220" 5054550

ABSTRACT OF THE DISCLOSURE

The invention relates to a system (20) for adaptation/optimization of the speed of a rotating electric machine (22) included in the system (20), ~~which wherein~~ the machine is intended to be directly connected to a distribution or transmission network (24). The machine (22) ~~comprises~~ has at least two electric windings, each of which ~~comprises~~ is formed from at least one electric conductor, a first semiconducting layer (14) arranged surrounding the conductor, an insulating layer (16) arranged surrounding the first semiconducting layer (14), and a second semiconducting layer (18) arranged surrounding the insulating layer (16). In addition, the system (20) ~~comprises means (26) which is configured to generate~~ the resultant stator and air gap flux of the machine (22) during operation, which wherein the flux is composed of at least two vectorial quantities.

# LIST OF RELATED CASES

Docket No	Client Ref	Application No	Patent No	Issue Date	PCT No	Filing Date	Status
					PCT/SE97/008	17-Feb-99	Pending
09847-0001-6X	8025	09/147,325					
					PCT/SE97/008	08-Feb-99	Pending
09847-0002-6X	8026	09/147,324					
					PCT/SE97/009	09-Feb-99	Pending
09847-0003-6X	8030	09/147,319					
					PCT/SE97/009	02-Feb-99	Pending
09847-0004-6X	8031	09/147,320					
					PCT/SE97/008	02-Mar-99	Pending
09847-0005-6X	8039	09/147,323					
					PCT/SE97/009	24-Feb-99	Pending
09847-0006-6X	8086	09/147,318					
					PCT/SE97/009	17-Feb-99	Pending
09847-0007-6X	8088	09/147,322					
					PCT/SE97/009	27-Nov-98	Pending
09847-0008-6X	8163	09/147,321					
					PCT/SE97/018	24-Jun-99	Pending
09847-0009-6X	8090	09/297,570					
					PCT/SE97/018	01-Jul-99	Pending
09847-0010-6X	8099	09/297,631					
					PCT/SE97/021	17-Jun-99	Pending
09847-0011-6X	ENKEL 8129	09/319,923					
					PCT/SE97/021	15-Oct-99	Pending
09847-0012-6X	ENKEL 8379	09/319,924					
					PCT/SE97/021	14-Oct-99	Pending
09847-0013-6X	ENKEL 8384	09/319,925					
					PCT/SE97/008		Inactive
09847-0014-6X	ENKEL 8247						
					PCT/SE97/008	15-Oct-99	Pending
09847-0015-6X	ENKEL 8248	09/319,922					
					PCT/SE97/008	15-Oct-99	Pending
09847-0016-6X	ENKEL 8249	09/319,926					
					PCT/SE97/008	14-Oct-99	Pending
09847-0017-6X	ENKEL 8250	09/319,921					
					PCT/SE98/001	01-Nov-99	Pending
09847-0018-6X	ENKEL 8167	09/355,797					
					PCT/SE98/001	01-Nov-99	Pending
09847-0019-6X	ENKEL 8168	09/355,855					
					PCT/SE98/001	14-Oct-99	Pending
09847-0020-6X	ENKEL 8138	09/355,801					
					PCT/SE98/001	22-Oct-99	Pending
09847-0021-6X	ENKEL 8139	09/355,795					
					PCT/SE98/001	25-Oct-99	Pending
09847-0022-6X	ENKEL 8140	09/355,807					

Docket No	Client Ref	Application No	Patent No	Issue Date	PCT No	Filing Date	Status
09847-0023-6X	ENKEL 8141	09/355,856			PCT/SE98/001	21-Oct-99	Pending
09847-0024-6X	ENKEL 8142	09/355,857			PCT/SE98/001	26-Oct-99	Pending
09847-0025-6X	ENKEL 8143	09/355,805			PCT/SE98/001	17-Sep-99	Pending
09847-0026-6X	ENKEL 8144	09/355,806			PCT/SE98/001	26-Oct-99	Pending
09847-0027-6X	ENKEL 8145	09/355,794			PCT/SE98/001	22-Oct-99	Pending
09847-0028-6X	ENKEL 8146	09/355,754			PCT/SE98/001	25-Oct-99	Pending
09847-0029-6X	ENKEL 8147	09/355,854			PCT/SE98/001	25-Oct-99	Pending
09847-0030-6X	ENKEL 8148	09/355,771			PCT/SE98/001	25-Oct-99	Pending
09847-0031-6X	ENKEL 8352	09/355,773			PCT/SE98/001	03-Aug-99	Pending
09847-0032-6X	ENKEL 8353	09/355,796			PCT/SE98/001	03-Aug-99	Pending
09847-0035-6X	ENKEL 8294	09/508,684			PCT/SE98/017	28-Mar-00	Pending
09847-0036-6X	ENKEL 8295	09/508,685			PCT/SE98/017	28-Mar-00	Pending
09847-0037-6X	ENKEL 8296	09/508,687			PCT/SE98/017	28-Mar-00	Pending
09847-0038-6X	ENKEL 8297	09/508,678			PCT/SE98/017	28-Mar-00	Pending
09847-0039-6X	ENKEL 8298	09/508,688			PCT/SE98/017	28-Mar-00	Pending
09847-0040-6X	ENKEL 8299	09/508,676			PCT/SE98/017	28-Mar-00	Pending
09847-0041-6X	ENKEL 8300	09/508,679			PCT/SE98/017	28-Mar-00	Pending
09847-0042-6X	ENKEL 8301	09/508,681			PCT/SE98/017	28-Mar-00	Pending
09847-0043-6X	ENKEL 8302	09/508,677			PCT/SE98/017	28-Mar-00	Pending
09847-0044-6X	ENKEL 8303	09/508,683			PCT/SE98/017	28-Mar-00	Pending
09847-0045-6X	ENKEL 8304	09/508,682			PCT/SE98/017	28-Mar-00	Pending
09847-0046-6X	ENKEL 8305	09/508,689			PCT/SE98/017	28-Mar-00	Pending

Docket No.	Asea Ref.	PCT No.	U.S. No.	Date Filed
70553	8037	PCT/SE97/00874	08/973,019	11/28/97
70554	8137	PCT/SE97/00875	08/973,210	11/28/97
70555	8237	PCT/SE97/00879	08/952,993	11/28/97
70556	8238	PCT/SE97/00878	08/952,990	11/28/97
70557	8239	PCT/SE97/00884	08/973,017	11/28/97
70558	8240	PCT/SE97/00885	08/973,018	11/28/97
70559	8241	PCT/SE97/00886	08/952,996	11/28/97
70560	8242	PCT/SE97/00887	08/952,995	11/28/97
70561	8243	PCT/SE97/00888	08/973,308	11/28/97
70562	8244	PCT/SE97/00889	08/973,307	11/28/97
70563	8245	PCT/SE97/00890	08/973,306	11/28/97
70564	8246	PCT/SE97/00891	08/973,305	11/28/97
70722	8342	Filed in U.S. 1st	08/980,214	11/28/97
70854	8343	Filed in U.S. 1st	08/980,213	11/28/97
70855	8344	Filed in U.S. 1st	08/980,210	11/28/97
71256	8523	Filed in U.S. 1st	09/161,992	9/29/98
71257	8524	Filed in U.S. 1st	09/161,993	9/29/98
71500	8029	PCT/SE97/00901	09/194,577	11/27/98
71501	8252	PCT/SE97/00892	09/194,578	11/27/98
71502	8036	PCT/SE97/00905	09/194,562	11/27/98
71503	8027	PCT/SE97/00899	09/194,567	11/27/98
71504	8028	PCT/SE97/00900	09/194,564	11/27/98
71505	8034	PCT/SE97/00904	09/194,563	11/27/98
71506	8024	PCT/SE97/00896	09/194,568	11/27/98
71507	8032	PCT/SE97/00893	09/194,561	11/27/98
71508	8033	PCT/SE97/00894	09/194,579	11/27/98

71509	8035	PCT/SE97/00895	09/194,560	11/27/98
71510	8038	PCT/SE97/00876	09/194,566	11/27/98
71511	8149	PCT/SE97/00908	09/194,565	11/27/98
71861	8082	PCT/SE97/01839	09/297,608	5/4/99
71862	8083	PCT/SE97/01840	09/297,606	5/4/99
71863	8084	PCT/SE97/01842	09/297,605	5/4/99
71864	8089	PCT/SE97/01843	09/297,607	5/4/99
71865	8091	PCT/SE97/01841	09/297,609	5/4/99
71911	8378	PCT/SE97/02152	09/331,120	6/17/99
71912	8385	PCT/SE97/02153	09/331,119	6/17/99
71943	8352	PCT/SE98/00151		8/3/99
71944	8353	PCT/SE98/00152		8/3/99
71945	8150	PCT/SE98/00162		8/3/99
71946	8151	PCT/SE98/00163		8/3/99
71947	8154	PCT/SE98/00164		8/3/99
71948	8155	PCT/SE98/00165		8/3/99
71949	8157	PCT/SE98/00166		8/3/99
71950	8159	PCT/SE98/00167		8/3/99
71951	8160	PCT/SE98/00168		8/3/99
71952	8161	PCT/SE98/00169		8/3/99
71953	8162	PCT/SE98/00170		8/3/99
71954	8166	PCT/SE98/00171		8/3/99
71955	8169	PCT/SE98/00174		8/3/99
71956	8170	PCT/SE98/00179		8/3/99
71957	8171	PCT/SE98/00175		8/3/99
71958	8172	PCT/SE98/00176		8/3/99